


## Product Data Sheet

## Multipower Miniature Media Converters

First, choose your Multipower Miniature Media Converters (for a complete list of available models, see Ordering Information on page 4).



Miniature Media Converters with LFPT switch  
(LHC0xxA-Rx, LGC0xxA-Rx or LGC1xxA-Rx)

Optionally, you can mount up to 18 Multipower Miniature Media Converters in the PowerTray (part number LHC018A-AC-R2, shown below).



PowerTray, 18-Slot  
(LHC018A-AC-R2)

### Features

- Convert 10-, 100-, or 1000-Mbps copper ports to fiber optic cable.
- Bring fiber to the desktop more economically than fiber NICs.
- Compact size makes them easy to integrate.
- Autonegotiating for speed and duplex..
- All models include a Link Fault Pass-Through (LFPT) switch that turns LFPT off for troubleshooting.

# Multipower Miniature Media Converters Data Sheet

## Overview

Now it's easier than ever to bring fiber to your network, no matter if your network is spread across a business campus, a large industrial site, or over great distances and/or subjected to temperature extremes. The Multipower Miniature Media Converters bring fiber to the desktop.

### Good things, small packages.

Multipower Miniature Media Converters are easy to install (literally plug-and-play), tiny enough to fit in anywhere, and very economical.

Use them to bring fiber to the desktop or add fiber segments to your network to gain extra distance—up to 24.85 miles (40 km) with Singlemode fiber.

### Twice the conversion power!

A Multipower Miniature Media Converter enables you to connect 10/100/1000-Mbps twisted-pair network segments to fiber optic cabling. It's both a media and data rate converter with 10/100/1000 auto-negotiation on the twisted-pair port. The fiber port operates at 100 Mbps or 1000 Mbps, depending on model.

All Multipower Miniature Media Converters have an HDX/FDX function for half- and full-duplex autosensing.

### Installation is easy.

Just connect a Multipower Miniature Media Converter to the RJ-45 connector on your PC's 10/100/1000-Mbps Ethernet port using CAT5e cable, then connect fiber optic cable to the other side of the media converter.

What's more, these tiny converters tuck unobtrusively behind your PC.

### Go the distance with fiber.

Multipower Miniature Media Converters using multimode fiber support distances of up to 984.2 feet (300 m) or 1.2 miles (2 km)—enough distance for most LAN applications. For more extensive campus applications, choose Singlemode or Singlemode, Single-Strand models for long-distance runs of up to 6.2, 12.4, 24.85 (10, 20, or 40 km).


### Three power options.

Multipower Miniature Media Converters can be powered one of three ways: by an external AC power supply included with each unit, by an optional USB Power Adapter Cable that plugs into a PC's USB port, or by an optional rackmount PowerTray.

The AC power supply is a universal external transformer that requires a nearby AC power outlet. The PowerTray provides power for up to 18 converters in only 1.5U of rack space. Rackmount ears are included.

## Typical application.

Multipower Miniature Media Converters extend your 10/100/1000BASE-T network beyond the 328-foot (100-m) limit—perfect for connecting remote workstations.



## Specifications

<b>Operating Environment</b>	Temperature: 32 to 122° F (0° to 50° C); Humidity: 5 to 95%, noncondensing
<b>Standards/Approvals</b>	IEEE 802.3, IEEE 802.3u, CE, RoHS
<b>User Controls</b>	(1) LFPT switch
<b>Connectors</b>	Copper side: (1) RJ-45; Fiber side: ST or SC: LHC040A-R4, LHC013A-R4, LHC036A-R4: (1) pair of ST®; LHC041A-R4, LGC010A-R2–LGC011A-R2, LGC120A-R4–LGC126A-R4: (1) pair of SC; LHC042A-R4–LHC043A-R4, LHC028A-R3–LHC029A-R3, LGC014A-R2–LGC015A-R2: (1) SC; LGC300A-R2 (SFP-to-SFP model): (2) SFP, (1) AC power, (1) 4-terminal DC power
<b>Power</b>	From the included external 100 – 240-VAC, 50 – 60-Hz, autosensing adapter; Via the optional USB Power Adapter Cable (LHC021A) connected to computer's USB port; From the optional PowerTray with a 100 – 240 VAC, 50 – 60-Hz (LHC018A-AC-R2) power supply; Draw: 96 watts, fully loaded; AC: Input: External 100–240-VAC, 50–60-Hz, autosensing power supply with country-specific power clips; Output: 5 VDC, 2 amp, 10 watts
<b>Dimensions</b>	1.8"H x 0.8"W x 3.4"D (2 x 4.6 x 8.6 cm)
<b>Weight</b>	0.3 lb. (0.1 kg)

NOTE: The LHC040A-R4 and LHC041A-R4 use a 850-nm wavelength, so they meet the 100BASE-SX standard.

# Multipower Miniature Media Converters Data Sheet

## Ordering Information

Item	Code	Item	Code
Multipower Miniature Media Converters		10-/100-/1000-Mbps Copper to 1000-Mbps Duplex Fiber	
10-/100-Mbps Copper to 100-Mbps Duplex Fiber		Multimode, 850-nm/220 m	SC <b>LGC120A-R4</b>
Multimode, 850-nm/300 m	ST <b>LHC040A-R4</b>	Singlemode, 1310-nm 10 km	SC <b>LGC121A-R4</b>
	SC <b>LHC041A-R4</b>	40 km	SC <b>LGC122A-R4</b>
Multimode, 1300-nm 2 km	ST <b>LHC013A-R4</b>	10-/100-/1000-Mbps Copper to 1000-Mbps Single-Strand Fiber, 10 km	
	SC <b>LHC014A-R4</b>	(Order one of each.)	
Singlemode, 1310-nm 40 km	ST <b>LHC036A-R4</b>	Singlemode, 1310-nm TX/1550-nm RX	SC <b>LGC125A-R4</b>
	SC <b>LHC015A-R4</b>	Singlemode, 1550-nm TX/1310-nm RX	SC <b>LGC126A-R4</b>
10-/100-Mbps Copper to 100-Mbps Single-Strand Fiber, 2 km		<b>To power a single converter via your computer's USB port, order...</b>	
(Order one of each.)		USB Power Adapter Cable (for use with 10/100 converters)	
Singlemode, 1310-nm TX/1550-nm RX	SC <b>LHC042A-R4</b>	<b>To rackmount multiple Miniature Media Converters, order...</b>	
Singlemode, 1550-nm TX/1310-nm RX	SC <b>LHC043A-R4</b>	PowerTray, 18-Slot with AC Power	
10-/100-Mbps Copper to 100-Mbps Single-Strand Fiber, 20 km		<b>For DIN rail mounting, order...</b>	
(Order one of each.)		DIN Rail Clip	
Singlemode, 1310-nm TX/1550-nm RX	SC <b>LHC028A-R4</b>	<b>LHC018A-AC-R2</b>	
Singlemode, 1550-nm TX/1310-nm RX	SC <b>LHC029A-R4</b>	<b>LXC-DR</b>	
1000-Mbps Copper to 1000-Mbps Duplex Fiber			
Multimode, 850-nm/220 m	SC <b>LGC010A-R2</b>		
Singlemode, 1310-nm 10 km	SC <b>LGC011A-R2</b>		

## About Black Box:

Black Box® is a trusted IT solutions provider delivering cutting-edge technology solutions and world-class consulting services to businesses across the globe. The breadth of our global reach, continuous innovation, and depth of our expertise accelerate customer success by bringing people, ideas, and technology together to solve real-world business problems. Our IT infrastructure solutions, services, and products enable secure, flawless connectivity and meaningful collaboration for businesses in every major market across six continents. To learn more, visit the Black Box website at [www.blackbox.com](http://www.blackbox.com).

Follow the company on X, formerly known as Twitter @BlackBox\_ns. Black Box® and the Double Diamond logo are registered trademarks of BB Technologies, LLC.

## Disclaimer:

Black Box Network Services shall not be liable for damages of any kind, including, but not limited to, punitive, consequential or cost of cover damages, resulting from any errors in the product information or specifications set forth in this document and Black Box Network Services may revise this document at any time without notice.

© Copyright 2021, 2022, 2024. Black Box Corporation. All rights reserved. Black Box® and the Double Diamond logo are registered trademarks of BB Technologies, Inc. Any third-party trademarks appearing in this publication are acknowledged to be the property of their respective owners.