



COMMON

UTY\_LOS

LOW\_BAT

FAULT

NOTES:

1. CONTACT RATING: 48VDC / 1 AMP

2. UTILITY LOSS RELAY (RLY\_3) NORMAL STATE IS LISTED WHEN RELAY IS ACTIVE. (RELAY IS ACTIVE WHEN THE UPS IS ON)

3. TERMINAL WIRE SIZE: 16 ~ 26 AWG

4. TERMINAL TORQUE: 3.5 IN LB

FALCON ELECTRIC, INC.

5116 AZUSA CANYON ROAD IRVINDALE, CA 91706

Title: UA88246 DRY CONTACT RELAY CARD

Drawing #: SD80232

Revision: A

Size: B

Date:6/9/2022

Sheet: 1 of 1

Default Jumper Settings

Jumper #	Description	Default Position
J1	Utility Loss Common	Closed
J2	Utility Loss	2 - 3 (N.C.)
J3	Low Battery Common	Closed
J4	Low Battery	1 - 2 (N.O.)
J5	Remote Shutdown	2 - 3 (Internal Supply)
J6	Fault / Bypass Common	Closed
J7	Fault / Bypass	1 - 2 (N.O.)
J8	MBS / Bypass	1 - 2 (N.O.)
J9*	New / Old CPU	1 - 2 (SSG Model)
J10*	On Bypass Setting	2 - 3 (Enable)

\*DO NOT CHANGE DEFAULT JUMPER SETTING OR DAMAGE MAY RESULT