

Optolinx FCS-3312


10/100/1000BaseTX to 1000BaseFX Managed Media Converter




Features

- ▶ Complies with IEEE 802.3 10BaseT, 802.3u 100BaseTX/100BaseFX, 802.3z 1000BaseFX, & 802.3ab 1000BaseTX
- ▶ Store and Forward Switching Mechanism
- ▶ Auto-Crossover for MDI/MDIX in TP Port
- ▶ Auto-Negotiated Data Rate & Flow Control on TP Port
- ▶ Supports 4K MAC Address
- ▶ Supports 256K Byte Packet Buffer
- ▶ Supports Loop Back and Diagnostic Test Button
- ▶ Supports Redundancy with FCM-CHS2 Chassis
- ▶ Compatible with FCM-CHS2 Remote Module Management
- ▶ Remote Port Management Function
- ▶ IN-BAND Diagnostic (Loop-Back Test)
- ▶ Supports Broadcast Storm Blocking via FCM-CHS2
- ▶ Plug-and-Play Installation
- ▶ 5-Year Warranty


Specifications




Top View (SC)




Panel View (SC)




Top View (ST)



Panel View (ST)



Top View (WDM)



Panel View (WDM)



Side View



Rear View

► Specifications

Remote Port Management (Through FCM-CHS2)

State Monitor: Model/Media/Link/Speed/Duplex/Activity/Power
Port Configuration: Auto/Speed/Duplex/Flow Control/Storm Broadcast Blocking

Standard

IEEE 802.3 10BaseT
IEEE 802.3u 100BaseTX/FX
IEEE 802.3z 1000BaseFX
IEEE 802.3ab 1000BaseTX

Interface

10/100/1000Mbps: 1 x RJ45 port
1000Mbps FX: 1 x SC port

Optical Fiber

Multi-Mode: 50/125 μ m ~ 62.5/125 μ m
Single-Mode: 9/125 μ m ~ 10/125 μ m

Wavelength

FCS-3312SC: 850nm
FCS-3312SC-S1/S3: 1310nm
FCS-3312WA: TX-1310nm; RX-1550nm
FCS-3312WB: TX-1550nm; RX-1310nm

Typical Distance

FCS-3312SC: 550 m
FCS-3312SC-S1: 10 Km
FCS-3312SC-S3: 30 Km
FCS-3312WA/WB: 20 Km

Minimum TX Power

FCS-3312SC: -9.5 dBm
FCS-3312SC-S1: -9.0 dBm
FCS-3312SC-S3: -5.0 dBm
FCS-3312WA/WB: -9.0 dBm

Maximum TX Power

FCS-3312SC: -4.0 dBm
FCS-3312SC-S1: -3.0 dBm
FCS-3312SC-S3: 0.0 dBm
FCS-3312WA/WB: -2.0 dBm

Sensitivity

FCS-3312SC: -18.0 dBm
FCS-3312SC-S1: -21.0 dBm
FCS-3312SC-S3: -24.0 dBm
FCS-3312WA/WB: -21.0 dB

Link Budget

FCS-3312SC: 8.5 dB
FCS-3312SC-S1: 12.0 dB
FCS-3312SC-S3: 19.0 dB
FCS-3312WA/WB: 12.0 dB

MAC Table

4K

Memory Buffer

256K

Forward/Filter Rate

10M: 14,880/14,880 pps
100M: 148,800/148,800 pps
1000M: 1,488,000/1,488,000 pps

Redundancy

Supports Redundancy with FCM-CHS2 Chassis

LED

Power, FDX/COL, Speed, TP Link/ACT, FO Link/ACT, Status

Power

External Power Supply: Input AC 120V - 240V
Voltage Requirement: DC 12V

Power Consumption

4.2 Watts

Operation Temperature

0° C to 50° C (32° F to 122° F)

Storage Temperature

-20° C to 60° C (-4° F to 140° F)

Operation Humidity

5% to 90% (Non-condensing)

Mechanical

Casing: IP30 Metal Case
Dimension (W x H x D): 140 x 78 x 26 mm (5.51 x 3.07 x 1.02 in.)
Weight: 0.8 Kg (1.8 lbs)
Installation: DIN-Rail/Wall Mountable

Emission/Safety

FCC Class A, CE

Warranty

5-Year Warranty

► Ordering Information

FCS-3312SC

10/100/1000TX - 1000FX Managed Media Converter, Multi-Mode, SC, 550 m

FCS-3312SC-S1

10/100/1000TX - 1000FX Managed Media Converter, Single-Mode, SC, 10 Km

FCS-3312SC-S3

10/100/1000TX - 1000FX Managed Media Converter, Single-Mode, SC, 30 Km

FCS-3312WA-S2

10/100/1000TX - 1000FX Single-Strand Fiber (WDM), Managed Media Converter, Single-Mode, SC, 20 Km, TX-1310nm; RX-1550nm

FCS-3312WB-S2

10/100/1000TX - 1000FX Single-Strand Fiber (WDM), Managed Media Converter, Single-Mode, SC, 20 Km, TX-1550nm; RX-1310nm

FCM-CHS2-AC

16 Slot IN-BAND Managed Media Converter Chassis (with 1 AC Power)

Optional Accessories

CBF-SC01ST-MD

SC to ST Multi-Mode Duplex Fiber Cable (1 Meter)

CBF-SC01SC-MD

SC to SC Multi-Mode Duplex Fiber Cable (1 Meter)

CBF-SC01SC-SS

SC to SC Single-Mode Simplex Fiber Cable (1 Meter)

AD-SCM-STF-M

SC (Male) to ST (Female) Duplex Adapter (Multi-Mode)

AD-SCM-STF-S

SC (Male) to ST (Female) Duplex Adapter (Single-Mode)

FCS-BK

Mounting Brackets for FCS Modules

DIN-RAIL-KIT

DIN-Rail Mounting Kit

Antaira Technologies

Toll-Free: (877) 229-3665
Phone: (714) 671-9000
FAX: (714) 671-9944

e-Mail: info@antaira.com
Website: <http://www.antaira.com>

 **antaira**
www.antaira.com